

	Přístroj	Poznámka
1F0		
1T1	aT0354 22/0.40 In = 577 A Sr = 400 kVA Ik'' = 9.49 kA VN pojistky PM45, 22/25kV, 25A U2 = 231/400 V dU = 0.0 % uk = 6 % ip = 20.9 kA	
1Q2	BH630N-DTV3 In = 630 A IR = 575 A Icu = 36 kA IR = 575 A, restart = T(t), li = 4xIR io = 16.5 kA	
1B3	Sběrnice B = 1 (Ik'' = 9.49 kA) U = 400 V (Un - 0.0%) io = 16.5 kA	
1F4	PHNA2qG In = 200 A Icc = 120 kA Připojeno pomocí FSD2 io = 12.3 kA	
1L7	1-AYKY 3x240+120 Iz = 229.8 A tm = 50 ° C (Ik'' = 7.43 kA) 58 m v zemi (D) dU = 0.0 % I ² t < k ² S ² io = 11.3 kA	
1F9	PHNA2qG In = 125 A I1 = 120 kA Připojeno pomocí SPF2 io = 7.65 kA	
1B10	Sběrnice B = 1 (Ik'' = 7.43 kA) U = 400 V (Un - 0.1%) io = 7.65 kA	
1F11	PNA000qG In = 40 A I1 = 120 kA Připojeno pomocí SPF00 io = 3.00 kA	
1L16	CYKY4x10 Iz = 51.8 A tm = 38 ° C (Ik'' = 3.95 kA) 20 m v zemi (D) dU = 0.1 % I ² t < k ² S ² io = 2.64 kA	
1Q23	LTE-25B In = 25 A Icn = 50 kA* li = 112.50 A io = 2.64 kA	
1.25	Vývod P = 5.0 kW xB = 5.0 kW cos fi = 0.95 (Ik'' = 3.95 kA) I = 7.60 A U = 399 V (Un - 0.2%) B = 1 io = 2.64 kA	